



JXSK-11M-KELUAR



Test Before Installation

The JXSKY Emergency Light Series is equipped with a manual Emergency Light-up Mode, allowing users to verify the product's functionality prior to installation.

1. To activate this mode, press and hold the **Test Switch** for 3 seconds. The LED light will turn on to indicate proper operation.
2. To turn the light off, press and hold the **Test Switch** again for 3 seconds.

If the LED does not light up, the unit may be faulty and should be checked or replaced.

Installation Steps

1

Unfasten the **thumb screw** of both side of top casing. Then, use a test pen to **gently release** the **top cover** of the product casing.

2

Arrange the **wires** into the casing through the **indicated wire inlet** ($\varnothing_{max}:20mm$). Then, Connect **Neutral** and **Unswitched Live** wires.

For Recessed Mounting

a

Panel Preparation:
Cut a **rectangular hole** with dimensions of **558 mm (L) x 30 mm (W)** in the ceiling.

b

Install the **recessed bracket** to the product from below. Then, lift **all the mounting clips** and gently **insert the unit** into the **ceiling cut-out**.

For Ceiling Mounting:

a

Secure the **top cover** onto the **ceiling** using **2x M3/M4 self-tapping screws****. Then, assemble the **KELUAR sign** to the **secured top cover**.

**Sold separately

For Wall Mounting:

a

Assemble the **KELUAR sign** to the **top cover**. Then, attach the **2x L-brackets**** onto the casing and install the **assembly** to the **wall**.

**Sold separately

Safety Wire Installation (Recommended):

a

Attach a steel safety wire ($\varnothing1.25mm$) with cable lugs** ($\varnothing1.25--5mm$) to the emergency light. Fasten the **safety wire firmly** to the **ceiling structure**. ****Sold separately.**

Charge the battery for a minimum of 24 hours before using the luminaire as a safety/emergency lighting source.

The luminaire must be installed by a qualified electrician. Always disconnect the power supply before performing any wiring work. Ensure that the input voltage matches the specified voltage range of the product. Ensure that all wiring connections are secure and properly insulated. Before turning the power on, double-check that all wires are correctly connected. Failure to follow these instructions may void the product warranty.