



JXBK-11M-KELUAR



Test Before Installation

The JXSKY Emergency Light Series is equipped with a manual Emergency Light-up Mode, allowing users to verify the product's functionality prior to installation.

1. To activate this mode, press and hold the **Test Switch** for 3 seconds. The LED light will turn on to indicate proper operation.
2. To turn the light off, press and hold the **Test Switch** again for 3 seconds.

If the LED does not light up, the unit may be faulty and should be checked or replaced.

Installation Steps

1

Use a test pen to **gently release** the top cover of the product casing.

2

Arrange the wires into the casing through the desired **wire inlet** ($\varnothing_{\text{max}}:20\text{mm}$).

3

Connect **Neutral** and **Unswitched Live** wires.

4

Secure all **wires within the cable holder** to avoid blocking the light distribution.

5

Fasten the **back casing** (with wire connected) onto the **installation wall**.

6

Reinstall the **top cover** onto the secured **back casing**. Push **4x clips** into place by hearing clicks.

Charge the battery for a minimum of 24 hours before using the luminaire as a safety/emergency lighting source.

The luminaire must be installed by a qualified electrician. Always disconnect the power supply before performing any wiring work. Ensure that the input voltage matches the specified voltage range of the product. Ensure that all wiring connections are secure and properly insulated. Before turning the power on, double-check that all wires are correctly connected. Failure to follow these instructions may void the product warranty.

Product specifications may change without prior notice. Images are for illustration only.