



JXSLIM-11NM | JXSLIM-13NM



Test Before Installation

The JXSKY Emergency Light Series is equipped with a manual Emergency Light-up Mode, allowing users to verify the product's functionality prior to installation.

1. To activate this mode, press and hold the **Test Switch** for 3 seconds. The LED light will turn on to indicate proper operation.
2. To turn the light off, press and hold the **Test Switch** again for 3 seconds.

If the LED does not light up, the unit may be faulty and should be checked or replaced.

Installation Steps

1

Use a test pen to **gently release** the top and middle cover of the product casing.

3

Arrange the **wires** into the casing through the indicated **wire inlet** ($\varnothing_{\text{max}}:20\text{mm}$).

2

Disconnect the **LED module wire** from the main board. Once the wire is free, remove the top and middle covers from the casing.

4

Connect **Neutral and Unswitched Live** wires.

For Surface Model

a

Fasten the casing into the ceiling through its interior using **M3 self-tapping screws****.
**Sold separately

b

Reconnect the **LED module wire** to the main board. Reinstall the top and middle covers onto the casing to complete the assembly.

For Recessed Model

a

Panel Preparation:
Cut a rectangular hole with dimensions of **262 mm(L) x 70 mm(W)** in the ceiling.

b

Attach the **recessed springs** to **both sides** of the product and tighten them with the provided screws.

c

Lift the **mounting clips** on **both sides** of the emergency light and gently **insert** the unit into the **ceiling cut-out**.

d

Ensure the **spring clips retract** and **grip firmly** against the rear side of the ceiling panel.

Safety Wire Installation (Recommended):

a

Attach a steel safety wire ($\varnothing 1.25\text{mm}$) with cable lugs** ($\varnothing 1.25\text{--}5\text{mm}$) to the emergency light. Fasten the safety wire firmly to the ceiling structure. **Sold separately.

Charge the battery for a minimum of 24 hours before using the luminaire as a safety/emergency lighting source.

The luminaire must be installed by a qualified electrician. Always disconnect the power supply before performing any wiring work. Ensure that the input voltage matches the specified voltage range of the product. Ensure that all wiring connections are secure and properly insulated. Before turning the power on, double-check that all wires are correctly connected. Failure to follow these instructions may void the product warranty.

Product specifications may change without prior notice. Images are for illustration only.